

Forty series: speaker settings table

4008 Fullrange							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
50 Hz	24dB Butt	90 Hz	8,0dB	5	0.288	-	-
		130 Hz	-4,0dB	2.998	0.479		
		1kHz	-3,0dB	11.936	2.54		

4008 + SW							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
100Hz	24dB Butt	90 Hz	8,0dB	5	0.288	-	-
		130 Hz	-4,0dB	2.998	0.479		
		1kHz	-3.0dB	11.936	2.54		

4010MH Fullrange							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
45 Hz	24dB Butt	80Hz	5,0dB	1,41	0.479	-	-
		389Hz	-3,0dB	4,80	1.39		
		3.36kHz	-4.0dB	1.41	0.714		

4010MH + SW							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
90Hz	24dB Butt	80Hz	5,0dB	1,41	0.479	-	-
		389Hz	-3,0dB	4,80	1.39		
		3.36kHz	-4.0dB	1.41	0.714		

4012MH Fullrange							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
44,6Hz	24dB Butt	80Hz	4,0dB	1,41	1,00	-	-
		350Hz	-6,0dB	4,80	0,30		
		9kHz	3,0dB	1,41	1,00		

4012MH + SW							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
90Hz	24dB Butt	80Hz	4,0dB	1,41	1,00	-	-
		350Hz	-6,0dB	4,80	0,30		
		9kHz	3,0dB	1,41	1,00		

4015MH Fullrange							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
40Hz	24dB Butt	70Hz	5,0dB	7,21	0,20	-	-
		300Hz	-5,0dB	4,80	0,30		
		900Hz	-2,0dB	2,04	0,70		
		2,5kHz	-1,0dB	4,80	0,30		
		10kHz	3,0dB	1,41	1,00		

4015MH + SW							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
90Hz	24dB Butt	70Hz	5,0dB	7,21	0,20	-	-
		300Hz	-5,0dB	4,80	0,30		
		900Hz	-2,0dB	2,04	0,70		
		2,5kHz	-1,0dB	4,80	0,30		
		10kHz	3,0dB	1,41	1,00		

4030MH Fullrange							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
40Hz	24dB Butt	75Hz	2,0dB	1,41	1,00	-	-
		155Hz	-5,0dB	4,80	0,30		
		400Hz	-4,0dB	4,80	0,30		
		1,5kHz	2,0dB	1,41	1,00		
		5kHz	-3.5dB	2.87	0,50		

4030MH + SW							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
90Hz	24dB Butt	75Hz	2,0dB	1,41	1,00	-	-
		155Hz	-5,0dB	4,80	0,30		
		400Hz	-4,0dB	4,80	0,30		
		1,5kHz	2,0dB	1,41	1,00		
		5kHz	-3.5dB	2.87	0.50		

40SW15 - 40SW18 (Low Pass freq. 90 Hz)							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
42Hz	24dB Butt	65Hz	4,0dB	4,80	0,30	86Hz	24dB Butt

40SW15 - 40SW18 (Low Pass freq. 110 Hz)							
High Pass Filter		PEQ				Low Pass Filter	
Freq	Shape	Freq	Gain	Width		Freq	Shape
				Q	Oct		
42Hz	24dB Butt	65Hz	4,0dB	4,80	0,30	106Hz	24dB Butt